

μC Based AC DPM with Trip



AVFI-96 Or AVFT-96

- Microcontroller based, Single 4 Digit display
- Supply 100-260 VAC
- Size 96(w)x96(h)x65(d) mm
- True RMS Measurement
- Sample rate of 1000Hz.
- Input: AC Voltage 0-300VAC, 0-5 Ampere, Frequency 45.0 to 65.0 Hz
- Accuracy of 0.25% of full scale
- CT Primary ratio programmable from 1A to 200A
- CT Secondary ratio programmable from No & 1A to 1000A
- Measure frequency with a resolution of 0.1 Hz.
- Simultaneously measure Voltage, Current & Frequency
- Current, Voltage & Frequency Indication selection
- Auto scan with time setting or Manual Scan by key
- Relay output for Over & Under Voltage Setting (Optional)
- Relay output for Over & Under Current Setting (Optional)
- Control mode selection – Auto or Manual Reset

WAVE INSTRUMENTS LLP

L-45/9, Phase-3, Opp. Mazda Ltd., GIDC Naroda, Ahmedabad -382330, Gujarat – INDIA

☎ +91- 9722003425, ☎ +91-79-40043425, 📞 +91-7043003425

Email: waveinstruments@gmail.com, Website: <http://www.wavetronics.co.in>