

µC Based ATM Timer for Two AC



- WTM-1201-ATM....Size: 96(w)x96(h)x65(d) mm
- WTM-1001-ATM....Size: 96(w)x48(h)x110(d) mm
- WTM-1101-ATM....Size: 72(w)x72(h)x65(d) mm
- WTM-1301-ATM....Size: 48(w)x48(h)x85(d) mm

- Microcontroller based, 4 Digit display
- Supply 100 - 260 V Ac
- Output: (1) Relay1(AC1) Contact , (2) Relay2 (AC2) Contact
- AC-1 Time 0001 to 9999 Minute as per range adjustable in set mode.
- AC-2 Time 0001 to 9999 Minute as per range adjustable in set mode.
- Fix 10 or 60 Second Delay between two AC
- Fix Power on delay 10 or 60 Second
- Power down memory of Time & AC
- Reset by Enter key in run mode
- Count Down Time

WAVE INSTRUMENTS LLP

L-45/9, Phase-3, Opp. Mazda Ltd., GIDC Naroda, Ahmedabad -382330, Gujarat – INDIA

☎ +91- 9722003425, ☎ +91-79-40043425, 📞 +91-7043003425.

Email: waveinstruments@gmail.com, Website: <http://www.wavetronics.co.in>