

µC Based Timer with On, Off & Total time setting



- WTM-2201-OF....Size: 96(w)x96(h)x65(d) mm
- WTM-2001-OF....Size: 96(w)x48(h)x110(d) mm
- WTM-2101-OF....Size: 72(w)x72(h)x65(d) mm
- WTM-2301-OF....Size: 48(w)x48(h)x85(d) mm

- Microcontroller based, Dual display
- Supply 220 V Ac
- Output: (1) On Relay Contact , (2) Off Relay Contact & (3) Buzzer Output(Optional)
- On Time 1 to 9999 as per range adjustable in set mode.
- Off Time 1 to 9999 as per range adjustable in set mode.
- Total Time 0000 to 9999 as per range adjustable in set mode.
- Unit Minute or Second Selectable
- Resolution 1 or 0.1 Selectable
- Power on start from Off time or On time selection
- Power down memory selection
- Total time Count Up (if you set total time=0000) in run mode.
- Total time Count Down (if you set total time>0000) in run mode.
- Alarm for process end with mute facility by Shift key.
- Reset by Enter key in run mode
- End Message @ Process complete.

WAVE INSTRUMENTS LLP

L-45/9, Phase-3, Opp. Mazda Ltd., GIDC Naroda, Ahmedabad -382330, Gujarat – INDIA

☎ +91- 9722003425, ☎ +91-79-40043425, 📞 +91-7043003425.

Email: waveinstruments@gmail.com, Website: <http://www.wavetronics.co.in>